



Model: PS 3240 / PS 3360 / PS 3480



Description

240 / 360 / 480 Watt mixer amplifier with rack mount ears (3U)

Integral module slot enables a dedicated tuner, cassette player, tuner/cassette, CD player, CD/ tuner or digital message module to be fitted.

- Rated output 240W or 360W (RMS)
- “Vox priority” on input 1 mutes inputs 2~aux, Pack Signal
- “Chime + Mute” contact on input 2-4
- Detachable screw terminals for input 2-4
- Mic/Line switch for input 2-4
- Phantom switch on input 1-4
- Mic input surge-protection
- Pre out/Amp in
- RCA socket for input 5-7 (aux selector)
- Slot for input modules
- Bass-treble tone control (100Hz, 10KHz)
- 5 speaker zone attenuator
- Connection of paging microphone (JPS-10)
- Variable speed fan
- Over current protection
- Thermal protection & short circuit protection
- AC operation – DC 24V operation

Specification:

Model	PS 3240	PS 3360	PS 3480
Rated output (RMS)	240W	360W	480W
Output impedance	70V,100V, 8Ω		
THD at 1kHz	Less than 0.4% (1kHz)		
Frequency response (±3dB)	35Hz~19kHz		
Signal to noise ratio	Line: Better than 70dB, Mic: Better than 60dB		
Input	Mic 1-4: 2.45mV, Line : 245mV, Aux: 245 mV		
Weight (kg)	16.5	19.0	21.0
Dimensions (W x H x D) mm	430 x 133 x 352		
Power requirement	230V AC 50/60Hz or 24V DC		