

Copper Modules

SFP0-01-25-XXXT-0-1
SFPX-08-10-XXXT-0-03

1Gbps & 10Gbps Copper Modules RJ45 SFP



SIL-SFP0-01-25-XXXT-0-1
1Gbps RJ45 Copper SFP, 100m



SIL-SFPX-08-10-XXXT-0-03
10Gbps RJ45 Copper SFP, 30m

OVERVIEW

The SilverNet SFP0-01-25-XXXT-0-1 supports 10/100/1000 Mbps data rate over Cat5 cable with an RJ45 connector interface. It allows communication over twisted-pair up to 100m. The SilverNet SFPX-08-10-XXXT-0-03 supports 10G BASE-T data rate over Cat6a/7 cable with an RJ45

connector interface. It allows communication up to 30m. Our copper modules are commonly used for transmitting data over a short distance and can be used for servers, switches, LANs in data centres, uplinks and many more applications.

Features

- Support 1000BASE-T & 10G BASE-T operation respectively
- 100m Reach over Cat5 UTP Cable
- Up to 30m reach over Cat6a/7 Cable
- Hot Pluggable SFP Footprint
- Fully metallic enclosure for low EMI
- Low power dissipation (1.05 W typical & 2.5 W typical respectively)
- Compact RJ-45 connector assembly
- Access to physical layer IC via 2-wire serial bus
- Compliant with SFP MSA specification
- Compliant with IEEE 802.3
- Operating temperature and humidity:
 - 5°C to +85°C
 - 5 - 95% non-condensing
- Storage temperature:
 - 40°C to +85°C

Part Code	Description
SIL-SFP0-01-25-XXXT-0-1	1Gbps RJ45 Copper SFP, 100m
SIL-SFPX-08-10-XXXT-0-03	10Gbps RJ45 Copper SFP, 30m

Copyright © SilverNet Limited. All rights reserved. All other company and product names may be trademarks of their respective companies. Whilst every effort is made to make sure the information shown is accurate, SilverNet Limited can not accept liability for any errors that may arise. No freedom to use information, patents, trademarks or other intellectual property rights is implied by the publication of this document. E&OE. SilverNet Limited reserve the right to change specifications and other information within this document without notice and your attention is brought to the fact that performance figures are under ideal conditions. Actual performance will depend on many environmental factors and it is recommended that a site survey is undertaken prior to installation. Please also note that this equipment may also be subject to local legislative restrictions. It is the end users responsibility to ensure that the installation complies with any such restrictions that are in force.



Distributed By: